

Model 601C

High-Voltage Power Amplifier



The Model 601C is a DC-stable, high-voltage power amplifier designed to provide precise control of output voltages in the ranges of 0 to ± 500 V, 0 to -1 kV, or 0 to +1 kV DC or peak AC, with an output current in the range of 0 to ± 10 mA DC or 0 to ± 20 mA peak AC. The Model 601C can have up to two (2) independent amplifier channels in one enclosure. Some industrial applications for the Model 601C include driving piezoelectric actuators, modulating electrooptics, and electrostatically controlling ion beams.

The Model 601C features an all solid-state design for high slew rate, wide bandwidth, and low-noise operation. The four-quadrant, active output stage sinks or sources current into reactive or resistive loads throughout the output voltage range. The Model 601C has a Dynamic Adjust feature which can be used to optimize the AC response of the output signal. These features are essential for achieving the accurate output response and high slew rates demanded by reactive loads.

The Model 601C is protected against overvoltage and overcurrent conditions that may be generated by active loads or by output short circuits to ground. Precision voltage and current monitors provide low-voltage representations of the high-voltage output and load current for monitoring purposes or for use as feedback signals in a closed-loop system.

The Digital Enable feature provides a connection for a remote device to turn ON and OFF the high voltage of the instrument. This makes the Model 601C suitable for automated or computer controlled systems.

The Model 601C can be operated as a noninverting or inverting amplifier with a fixed gain. The input gain of the 601C is factory set for 100 V/V. A gain of 50 V/V is available for the ± 500 V range only. If different output voltage ranges, input configurations, or voltage gain ratios are required, please contact Trek, Inc. for more information.

The Model 601C is available in single channel or dual channel configurations. These units can be operated on a bench top or, with optional hardware, in a standard 19-inch rack.

- Available voltage ranges
To ± 500 V DC or Peak AC
0 to -1 kV DC or Peak AC
0 to +1 kV DC or Peak AC

- DC Accuracy: better than 0.1% of full scale

- Slew Rate: greater than 50 V/ μ s

- Up to two independent amplifier channels in one enclosure

- Precision voltage and current monitors provide low-voltage representations of the output voltage and load current

- Remote high-voltage ON/OFF capability

- CE compliant



Measurement and Power Solutions™

www.trekinc.com

Model 601C Specifications

All specifications are with no load unless otherwise noted.

Output

Output Voltage Range*

Available in voltage ranges of
0 to ± 500 V, 0 to -1 kV, or 0 to +1 kV
DC or peak AC.

Output Current Range (all voltages)

0 to ± 10 mA DC.
0 to ± 20 mA peak AC.

Amplifier Input

Input Voltage Range

0 to ± 10 V DC or peak AC, noninverting.

Input Impedance

25 k Ω , nominal.

Performance

DC Voltage Gain*

100 V/V (a gain of 50 V/V is available
for the ± 500 V range only).

DC Voltage Gain Accuracy

Better than 0.1% of full scale.

Offset Voltage

Less than 500 mV.

Output Noise

Less than 10 mV rms (measured using
the true rms feature of the Hewlett
Packard Model 34401A digital
multimeter).

Slew Rate (10% to 90%, typical)

Greater than 50 V/ μ s.

Large Signal Bandwidth (1% distortion)

DC to 8 kHz.

Small Signal Bandwidth (-3dB)

DC to 30 kHz.

Settling Time to 1%

Less than 300 μ s for a 1 kV step.

Stability

Drift with Time

Less than 100 ppm/hr,
noncumulative.

Drift with Temperature

Less than 50 ppm/ $^{\circ}$ C.

Features

Voltage Monitor

A buffered output provides a low-voltage
replica of the high voltage output.

Scale Factor

1/100th of the high-voltage output.

DC Accuracy

Better than 0.1% of full scale.

Offset Voltage

Less than ± 5 mV.

Output Noise

Less than 10 mV rms (measured using
the true rms feature of the Hewlett
Packard Model 34401A digital
multimeter).

Output Impedance

0.1 Ω .

Current Monitor

A buffered output provides a low-voltage
representation of the load current.

Scale Factor

0.5 V/mA.

DC Accuracy

Better than 1 % of full scale.

Offset Voltage

Less than ± 10 mV.

Output Noise

Less than 20 mV rms (measured using
the true rms feature of the Hewlett
Packard Model 34401A digital
multimeter).

Output Impedance

0.1 Ω .

Output Voltage Configurations

Factory set for 0 to ± 500 V DC or peak AC.
Other available output voltage ranges are
0 to -1 kV or 0 to +1 kV DC or peak AC
This setting is customer specified.

Digital Enable

An input providing a connection for a
TTL compatible signal to turn on and
off the high-voltage output.

Features (cont.)

Input Configuration*

Factory set as a noninverting amplifier,
the Model 601C can be configured as an
inverting amplifier.

Dynamic Adjust

A graduated one-turn potentiometer is
used to optimize the AC response of the
Model 601C.

General

Dimensions

Single Channel Instrument

222.3 mm W x 108 mm H x 335 mm D
(8.75" W x 4.25" H x 13.2" D).

Dual Channel Instrument

433.8 mm W x 108 mm H x 335 mm D
(17" W x 4.25" H x 13.2" D).

Weight

Single Channel Instrument

4.3 kg (9.4 lb)

Dual Channel Instrument

8.6 kg (18.8 lb)

High-Voltage Output Connector

SHV high-voltage connector.

Power Requirements

Line Voltage

Factory set for one of two ranges: 90
to 127 V AC or 180 to 250 V AC, at 48
to 63 Hz (specify when ordering).

Power Consumption

150 VA, maximum.

Power Receptacle

Standard three-prong power connector
with an integral fuse holder.

* Specify when ordering or contact TREK, INC.

Copyright © 2011 TREK, INC.

All specifications are subject to change.
1122/DEC

Model 601C Ordering Information

Item	Part No.	Optional Accessories	Part No.
Power Amplifier/Piezo Driver (90 to 127 V AC)	601C-L	603RA Full Rack Mount Kit	C4036
Power Amplifier/Piezo Driver (180 to 250 V AC)	601C-H	603RA-2 Dual Instrument Full Rack Mount Kit	C4060
		604RA Half-Rack Mount Kit	C4008
The Model 601C comes from the factory with settings for an output voltage of ± 500 V DC or peak AC, a voltage gain ratio of 100 V/V, with a noninverting input. If more than one output voltage range, or voltage gain ratio is required, please contact TREK, INC. for more information.			
Included Accessories			
Operator's Manual	23146	Certification	
High-Voltage Output Cable Assembly (3 meters)	43874	TREK, INC. certifies that each Model 601C is tested and calibrated to specifications using measurement equipment traceable to the National Institute of Standards and Technology or traceable to consensus standards.	
Line cord (90 to 127 V AC)	N5002		
Line Cord (180 to 250 V AC)	Contact Factory		



TREK, INC. • 11601 Maple Ridge Road • Medina, NY 14103 • USA • 800-FOR TREK
585-798-3140 • 585-798-3106 (fax) • www.trekinc.com • sales@trekinc.com

